



Follower amplifier



- The output of a low frequency generator applied to the AS150 input, amplifies the voltage until 80V peak to peak, and the current up to 7A with an impedance $\geq 4\Omega$.
- Bandwidth at 0.1dB: 20Hz-20kHz. (at 0.7dB: 10Hz - 50kHz)
- The output level of the low frequency generator adjusts the AS150 output amplitude from 0 to 80VDC.
- The AS150 output is protected against overloads.

OTHER FEATURES

- Input on BNC terminal Two parallel outputs: on 2 $\varnothing 4$ mm terminals and on BNC
- AS150 does not amplify the low frequency generator DC component
- 100 – 240VAC 50-60Hz power supply
- Dimensions/weight: 500 x 300 x 65mm 4.7kg

ref. AS150



**COMPLETE RANGE
GENERATORS**

