



1MHz AC Millivoltmeter



ref. GVT417

GVT417 is a millivoltmeter for the measuring of sinusoidal voltages from 10 μ V to 100V, in the 10 Hz to 1MHz band. The dial is graduated in volts and dB for the direct measurement of amplifier increases.

RANGES V 300 μ V - 1 - 3 - 10 - 30 - 100 - 300mV 1 - 3 - 10 - 30 - 100V

RANGES dB -70 -60 -50 -40 -30 -20 -10 0 +10 +20 +30 +40 dB

ACCURACY 3 % from 20 Hz to 200kHz - 10% from 10 Hz to 1MHz

IMPEDANCE 1 M Ω - 40 pF

OVERLOAD from 300 μ V to 0,3V: 150VAC / from 1 to 100 VAC: 300 VAC

OUTPUT

A 100mVrms copy output for the full deviation allows the GVT417 to be used as an attenuator/ amplifier at a constant signal input level.

OTHER FEATURES

Power supply: 115-230VAC 50Hz.

Dim. 142 x 210mm.

Depth: 235mm

Weight: 3kg

CE11010 CATII CL1 300Vrms pol2



**COMPLETE RANGE
AMMETERS & VOLTMETERS**

